
Frog Type X +Zoom


inter•lux











Luminaire

- IP66 rated spot light with zoomable lens or fixed focus optics
- Adjustable and lockable spot light for illuminating exterior landscapes and highlighting growing shrubbery and trees.
- Surface mounted, ground spike or tree strap.
- Precision machined from 70 90% recycled
- 95+ CRI with multiple CCTs and optics available.

Mounting

- SM = Surface Mounted
- GS = Ground Spike¹
- TS = Tree Strap¹

Power²

- 8 = 8W (798lm initial at 250mA, 34.1Vf)
- 12 = 12W (1513lm initial at 350mA, 36.9Vf)

CCT (95+ CRI)3

- 927 = 2700K
- 930 = 3000K
- 935 = 3500K
- 940 = 4000K

Optic

- N = Narrow (19.2°), 12W Only
- M = Medium (26°), 12W Only
- F = Flood (34.6°), 12W Only
- WF = Wide Flood (53.1°), 12W Only
- $Z1 = Zoom 1 (17^{\circ} 44^{\circ}), 8W Only^{4}$
- Z2 = Zoom 2 (21° 44°), 12W Only⁴

Finish

- CB = Classic Bronze 34
- W = Pure White, RAL9010
- BL = Matte Black, RAL9005
- CF = Custom finish, specify RAL

Remote Driver⁵

(8W @ 250mA)

- ECO30W-250 = 0-10V EldoLED ECOdrive 30W for 1 fixture
- SOLO50W-250 = 0-10V EldoLED SOLOdrive 50W for 1-2 fixtures (1 per output)
- SOLO100W-250 = 0-10V EldoLED SOLOdrive 100W for 1-4 fixtures (1 per output)

(12W @ 350mA)

- ECO30W-350 = 0-10V EldoLED ECOdrive 30W for 1 fixture
- SOLO50W-350 = 0-10V EldoLED SOLOdrive 50W for 1-2 fixtures (1 per output)
- SOLO100W-350 = 0-10V EldoLED SOLOdrive 100W for 1-4 fixtures (1 per output)
- 1. See page 3 for details.
- 2. Wattage shown is for LED only, system wattage varies depending on driver selected
- See photometric data sheet for delivered lumens.
- 4. See page 4 for details
- 5. See driver information for details.

Ordering Information							
Model	Mounting	Power ²	CRI/ CCT ³	Optic	Finish	+	Driver ⁵
MS-FX	SM GS ¹ TS ¹	12	927 930 935 940	N M F WF	CB W BL CF		ECO30W-XXX SOLO50W-XXX SOLO100W-XXX
MS-FXZ (Zoom)		8		Z1 ⁴			
		12		Z2 ⁴			







