

















Photometry (4W)

Fitting	Polar diagram	LED	Supply	Power	Delivered output
 <p>4mm LES Very Narrow</p>		95 CRI, 3000K	Constant Current 450mA	3.9W	351lm

Photometry (8W)

Fitting	Polar diagram	LED	Supply	Power	Delivered output
 <p>6mm LES Very Narrow</p>		95 CRI, 3000K	Constant Current 250mA	7.9W	704lm
 <p>6mm LES Zoom Narrow</p>		95 CRI, 3000K	Constant Current 250mA	7.9W	695lm
 <p>6mm LES Zoom Wide</p>		95 CRI, 3000K	Constant Current 250mA	7.9W	696lm

Photometry (12W)

Fitting	Polar diagram	LED	Supply	Power	Delivered output
 9mm LES Very Narrow		95 CRI, 3000K	Constant Current 350mA	11.9W	1174lm
 9mm LES Medium		95 CRI, 3000K	Constant Current 350mA	11.9W	1125lm
 9mm LES Flood		95 CRI, 3000K	Constant Current 350mA	11.9W	1050lm
 9mm LES Wide Flood		95 CRI, 3000K	Constant Current 350mA	11.9W	1038lm