













## Photometry (4W)

Fitting	Polar diagram	LED	Supply	Power	Delivered output
 <p>4.5mm LES Narrow 1</p>		95 CRI, 3000K	Constant Current 450mA	3.9W	339lm

## Photometry (8W)

Fitting	Polar diagram	LED	Supply	Power	Delivered output
 <p>6mm LES Narrow 2</p>	 <p>17.8°</p>	95 CRI, 3000K	Constant Current 250mA	7.9W	639lm
 <p>6mm LES Medium</p>	 <p>23°</p>	95 CRI, 3000K	Constant Current 250mA	7.9W	639lm
 <p>6mm LES Flood</p>	 <p>34.6°</p>	95 CRI, 3000K	Constant Current 250mA	7.9W	593lm
 <p>6mm LES Wide Flood</p>	 <p>54.5°</p>	95 CRI, 3000K	Constant Current 250mA	7.9W	642lm
 <p>6mm LES Zoom (Wide)</p>	 <p>21.6°</p>	95 CRI, 3000K	Constant Current 250mA	7.9W	577lm